

Quantum information processing using frequency control of impurity spins in diamond

A.M. Zagoskin^{1,2}, J.R. Johansson², S. Ashhab² and Franco Nori^{2,3}

(1) Department of Physics and Astronomy,

The University of British Columbia,

Vancouver, B.C., V6T 1Z1 Canada

(2) Digital Materials Laboratory, Frontier Research System,

RIKEN, Wako-shi, Saitama 351-0198, Japan and

(3) Center for Theoretical Physics, Physics Department,

Center for the Study of Complex Systems,

The University of Michigan, Ann Arbor, MI 48109-1040, USA

Abstract

Spin degrees of freedom of charged nitrogen-vacancy (NV^-) centers in diamond have large decoherence times even at room temperature, can be initialized and read out using optical fields, and are therefore a promising candidate for solid state qubits. Recently, quantum manipulations of NV^- - centers using RF fields were experimentally realized. In this paper we show; first, that such operations can be controlled by varying the frequency of the signal, instead of its amplitude, and NV^- - centers can be selectively addressed even with spatially uniform RF signals; second, that when several NV^- - centers are placed in an off-resonance optical cavity, a similar application of classical optical fields provides a controlled coupling and enables a universal two-qubit gate (CPHASE). RF and optical control together promise a scalable quantum computing architecture.

I. INTRODUCTION

Impurity spins in diamond are among the most promising candidates for solid state quantum hardware. The so called (negatively charged) nitrogen-vacancy centers (NV^-) have a low-lying spin triplet state 3A with a large decoherence time (up to $\sim 350\mu\text{s}$) at room temperature, which can be initialized and read out using a strong, spin-conserving optical transition to the excited 3E state [1, 2, 3, 4, 5, 6]. The coherent manipulation of the 3A state and its coupling to spins of ^{13}C [2, 6] and N [4, 5] demonstrated the feasibility of NV^- -based quantum devices. Though the direct coupling of different NV^- - centers, necessary for a scalable architecture, would require placing them too close to each other (within a few nm), coupling through an optical mode is possible [7, 8, 9] using Stark shifts, in order to tune the coupling on and off. (Stark shifts in NV^- were observed in bulk response [10, 11, 12] as well as from individual centers [13].)

The use of local time-dependent fields for selective control is a natural approach, but it is not always easily achieved in the case of microscopic qubits. Here we suggest an approach which would allow us to address specific NV^- - centers by tuning to their resonant frequency, which can be made position-dependent by the application of a *static* nonuniform magnetic field. We will also show that a similar approach using classical optical fields allows controlled coupling and universal two-qubit gates for NV^- - centers in an optical cavity.

II. MODEL

An NV^- - center is a negatively charged complex of a nitrogen impurity and a neighbouring vacancy. It can be formed as a result of nitrogen implantation in the diamond matrix; in experiments so far, the conversion from N to NV^- was achieved with a limited efficiency of about 5% [4]. It is therefore common to find an NV^- - center close to a nitrogen impurity. Unlike an NV^- - center, a nitrogen impurity does not have an electric dipolar moment and does not couple to optical fields. Consider such a N- NV^- complex [4, 5]. Let us choose the [111]-direction as the z -axis. The magnetic moment (spin 1) of the NV^- - center and the eigenvalues of its z -component are $\vec{S}$, $M_z = 0, \pm 1$; for the N impurity (spin 1/2) they are denoted respectively by $(1/2)\vec{\sigma}$, $m_z = \pm 1/2$; $\vec{\sigma}$ is the vector of Pauli matrices. The 3A ground state of the NV^- -center is split by the crystal field, while the ($M_z = \pm 1$)-states are

degenerate, and the ($M_z = 0$)-state becoming the true ground state. The ($M_z = 0$)-state is also the state leading to enhanced photoluminescence (through the excitation to 3E and subsequent decay through a metastable level 1A (see e.g. [14]), allowing an optical readout [2, 3, 4, 5]. The external magnetic field along the z -axis splits the ($M_z = \pm 1$)-states as well as the ($m_z = \pm 1/2$)-spin states of the nitrogen impurity. The Hamiltonian of the system is (in the absence of an electric field)

$$H = H_{NV} + H_N + H_{\text{int}}, \quad (1)$$

where

$$H_{NV} = D(S_z)^2 + \kappa \vec{B} \cdot \vec{S}, \quad (2)$$

$$H_N = \frac{1}{2} \kappa \vec{B} \cdot \vec{\sigma} + A \vec{\sigma} \cdot \vec{I}. \quad (3)$$

Here $D = 2.88$ GHz [15, 16, 17], $\kappa = 2.8$ MHz/Gs [4, 5], the hyperfine splitting $A = 86$ MHz or 114 MHz depending on the position of the nitrogen in the lattice [18], and $\vec{I}$ is its nuclear spin ($I = 1$). The magnetic dipolar interaction

$$H_{\text{int}} = \gamma [\vec{S} \cdot \vec{\sigma} - 3(\vec{S} \cdot \vec{n})(\vec{\sigma} \cdot \vec{n})] \quad (4)$$

has a scale $\gamma \approx 6.5$ MHz for the distance between NV^- and N of 2 nm; $\vec{n}$ is the unit vector in the direction connecting N and NV^- .

When $B_z = B_{\text{res}} = 514$ Gs, the transition ($M_z = 0$) $\leftrightarrow$ ($M_z = -1$) in the NV^- - center is in resonance with the transition ($m_z = +1/2$) $\leftrightarrow$ ($m_z = -1/2$) in N. The term (4) then induces coherent transitions in the system, which were experimentally observed in [4, 5]. Other resonances, shifted by ~ 15 Gs to either side due to the hyperfine interaction in N, were also observed. (The hyperfine splitting in the NV^- - center was too small to be resolved [5]; we neglect it here.)

In order to distinguish different NV^- - centers, we now consider the application of a B_z -field gradient. For example, if they are placed $10 \mu\text{m}$ apart, a field gradient of 1 T/cm will produce a 30 MHz difference in the ($M_z = 0$) $\leftrightarrow$ ($M_z = -1$) transition frequency between the neighbouring centers, which is enough for our purposes, as we shall see below.

III. RF CONTROL OF SINGLE-SPIN ROTATIONS IN NV^- - CENTERS

If the field $B_z \neq B_{\text{res}}$, the transitions ($M_z = 0; m_z = 1/2$) $\leftrightarrow$ ($M_z = -1; m_z = -1/2$) are suppressed. (Note that these energy conserving transitions do not conserve spin.) Single-

qubit operation on a NV^- - center can be then performed by applying a *spatially uniform* AC field along the y -axis, with the resonance frequency $\omega_y = D - \kappa B_z$ (of order of 1.5 GHz) corresponding to the $(M_z = 0) \leftrightarrow (M_z = -1)$ -transitions:

$$H_y = \kappa B_y \cos \omega_y t S_y. \quad (5)$$

Due to the B_z -gradient, this frequency is different for different NV^- - centers, and we have a *frequency-based* control. First, we go to the interaction representation:

$$H_y \rightarrow U_{NV} H_y U_{NV}^\dagger, \quad (6)$$

where

$$U_{NV} = \exp[iH_{NV}t] = (1 - S_z^2) + (S_z^2 \cos \kappa B_z t + i S_z \sin \kappa B_z t) \exp[iDt]. \quad (7)$$

After dropping the fast rotating terms (rotating wave approximation, RWA), we obtain the effective Hamiltonian

$$H_{y,\text{eff}} = \frac{\kappa B_y}{2} \left[\frac{S_y - [S_z, S_y]_+}{\sqrt{2}} \right] \equiv \frac{\kappa B_y}{2} \sigma_y^{NV}. \quad (8)$$

The operator in brackets acts as the Pauli matrix σ_y on the subspace $\{M_z = 0, M_z = -1\}$. The AC field produces relatively fast rotations of a chosen NV^- - center, in excess of 1 MHz/G.

The use of frequency instead of amplitude RF control is not dictated by the fact that the latter would require a local (within few microns) application of RF fields. The latter is feasible [19] and, on a little larger scale, is being done in experiments with superconducting flux and phase qubits on a regular basis (see e.g. [20]). Nevertheless the frequency control [21] has certain advantages including, but not limited to, less complex circuitry.

IV. RF CONTROL OF NV^- -N COUPLING

A relatively weak AC field with appropriate frequency can turn on the transitions $(M_z = 0; m_z = 1/2) \leftrightarrow (M_z = -1; m_z = -1/2)$. To see this, we again perform a unitary transformation of the Hamiltonian to the interaction representation,

$$H \rightarrow U_N U_{NV} H U_{NV}^\dagger U_N^\dagger - i U_N U_{NV} \frac{\partial}{\partial t} [U_{NV}^\dagger U_N^\dagger], \quad (9)$$

where U_{NV} was defined in (7), and

$$U_N = \exp[iH_N t] = \cos[(\kappa B_z + AI_z)t/2] + i\sigma_z \sin[(\kappa B_z + AI_z)t/2]. \quad (10)$$

The resonance condition for the transition $(M_z = 0; m_z = 1/2) \leftrightarrow (M_z = -1; m_z = -1/2)$ is $2\kappa B_z + AI_z - D = 0$. Assuming a detuning $\delta\omega$ from resonance, i.e.

$$2\kappa B_z + AI_z - D = \delta\omega, \quad (11)$$

we find (from Eq. (9)) the effective interaction

$$H_{\text{eff}} = \gamma(1 - 3n_z^2)S_z\sigma_z + \frac{\cos(\delta\omega t)}{2\sqrt{2}}\gamma(2 - 3n_x^2 - 3n_y^2) [\sigma_x^{NV}\sigma_x + \sigma_y^{NV}\sigma_y] + h(t) \quad (12)$$

(with the same notation as in Eq.(8)). Here $h(t)$ denotes the rest of the terms, which all are fast rotating and should be dropped in the RWA. So is the second term in the r.h.s. of (12), unless the detuning $\delta\omega$ can be compensated. This is done by an additional field along the z -axis, $B'_z(t) = \eta\kappa B_z \sin \omega t$. (The corresponding term in the Hamiltonian is not affected by the transformation (9)). After one more unitary transformation,

$$H_{\text{eff}} \rightarrow U' H_{\text{eff}} U'^{\dagger} - iU' \frac{\partial}{\partial t} [U'^{\dagger}], \quad (13)$$

with

$$U = \exp \left[-i\eta \kappa B_z (S_z + \frac{1}{2}\sigma_z) \cos(\omega t)/\omega \right], \quad (14)$$

and assuming $\omega = \delta\omega$, we obtain, in the RWA, the following Hamiltonian:

$$\tilde{H}_{\text{eff}} = \gamma(1 - 3n_z^2)S_z\sigma_z + \frac{J_1(2\eta\kappa B_z/\omega)}{2\sqrt{2}}\gamma(2 - 3n_x^2 - 3n_y^2) [\sigma_x^{NV}\sigma_x + \sigma_y^{NV}\sigma_y]. \quad (15)$$

Otherwise the effective coupling is zero. Here J_1 is a Bessel function. This result, frequency-controlled NV⁻-N coupling, is confirmed numerically (Figs. 1,2).

The coupling strength in resonance, $\gamma \approx 6.5$ MHz, determines how far we should be off resonance in order to achieve decoupling. This frequency is large enough to justify the approximations leading to (15). The coupling is switched on by an AC field $B'_z(t)$. The coupling strength will be smaller than γ , but not drastically. Even choosing $\delta\omega = 0.2$ GHz, $\eta = B'_z/B_{\text{res}} = 0.05$, and remembering that $\kappa B_{\text{res}} \approx 1.5$ GHz, we find the attenuation of the coupling strength ≈ 0.32 . It will still produce coherent transitions at ~ 2 MHz, which is fast compared to the decoherence times at room temperature as high as 0.35 ms.




FIG. 1: Maximum occupation probability for the NV^- - center ground state, $\max \rho_{00}^{\text{NV}}$, when initially in the excited state, as a function of the AC field frequency, ω , for the NV^- -N detuning $\delta\omega = 0.2$ GHz and the AC field amplitude $\kappa B'_z = 67$ MHz (corresponding to $\eta = 0.05$, with static field amplitude $\kappa B_z = 1.34$ GHz); $\gamma = 6.5$ MHz. Note additional peaks at integral fractions of $\delta\omega$, which correspond to the higher-order (multi-photon) processes, dropped from Eq. (15).




FIG. 2: (Color online) The occupation probabilities of the NV^- - center ground state $M_z = 0$ (dashed line in blue) and the excited state $M_z = -1$ (in green) as a function of time, for the same choice of parameters as in Fig. 1, and $\omega = 0.2$ GHz. The transition frequency (≈ 2 MHz) agrees with the RWA value following from Eq. (15).

As an aside, in the same way, one can show that when the system is in resonance, an AC field $B'_z(t)$ will suppress the transitions and freeze the spins in NV^- and N (coherent destruction of tunneling, see e.g. [22]). This is not useful to the coupling scheme we are describing here.

In order to perform arbitrary one-qubit rotations of nitrogen spins, as well as two-qubit gates between NV^- and N, we only need to initialize NV^- and perform single-qubit rotations on it (see e.g. [23], where the phase qubit is analogous to an NV^- - center, and the quantum

two-level system to a N impurity spin), which can be done using the RF control (Eq. (8)).

V. NV⁻-NV⁻ AND INDIRECT N-N COUPLINGS

The scalability of the design requires the coupling between different NV⁻- centers or NV⁻-N complexes. For macroscopic qubits this is done through the magnetic flux or charge coupling to the cavity modes [23, 24, 25, 26]. In our case, unfortunately, the magnetic coupling is way too weak. Instead, we can use an optical cavity mode and two classical laser fields, along the lines of Refs. 8, 27. This has the disadvantage of involving the ³E state, where the decoherence rate is higher. On the other hand, the laser fields are easier to apply locally. By tuning the frequency of the laser field, the interaction strength can be controlled.

Consider two NV⁻- centers placed in an off-resonance optical cavity. The Hamiltonian of the system is

$$H = H_0 + H_{\text{field}} + H_{\text{cavity}}, \quad (16)$$

$$H_0 = \omega_c a^\dagger a + \frac{E}{2}(I + \sigma_1^z) + \left(\frac{E+\Omega_1}{2}I + \frac{E-\Omega_1}{2}\tau_1^z \right) + \frac{E}{2}(I + \sigma_2^z) + \left(\frac{E+\Omega_2}{2}I + \frac{E-\Omega_2}{2}\tau_2^z \right), \quad (17)$$

$$\begin{aligned} H_{\text{field}} = H_{\text{field},1} + H_{\text{field},2} = & g_{1x}^{(0)} \mathcal{E}_1^{(0)} \cos(\omega_1^{(0)} t) \sigma_1^x + g_{1x}^{(-1)} \mathcal{E}_1^{(-1)} \cos(\omega_1^{(-1)} t) \tau_1^x \\ & + g_{2x}^{(0)} \mathcal{E}_2^{(0)} \cos(\omega_2^{(0)} t) \sigma_2^x + g_{2x}^{(-1)} \mathcal{E}_2^{(-1)} \cos(\omega_2^{(-1)} t) \tau_2^x, \end{aligned} \quad (18)$$

$$\begin{aligned} H_{\text{cavity}} = H_{\text{cavity},1} + H_{\text{cavity},2} = & g_{1z}^{(0)} \epsilon(a^\dagger + a) \sigma_1^z + g_{1z}^{(-1)} \epsilon(a^\dagger + a) \tau_1^z \\ & + g_{2z}^{(0)} \epsilon(a^\dagger + a) \sigma_2^z + g_{2z}^{(-1)} \epsilon(a^\dagger + a) \tau_2^z. \end{aligned} \quad (19)$$

Here the operators

$$\begin{aligned} \sigma_j^z &= |E_j\rangle\langle E_j| - |(A; M_z = 0)_j\rangle\langle (A; M_z = 0)_j|, \\ \tau_j^z &= |E_j\rangle\langle E_j| - |(A; M_z = -1)_j\rangle\langle (A; M_z = -1)_j|, \\ \sigma_j^x &= |E_j\rangle\langle (A; M_z = 0)_j| + |(A; M_z = 0)_j\rangle\langle E_j|, \\ \tau_j^z &= |E_j\rangle\langle (A; M_z = -1)_j| + |(A; M_z = -1)_j\rangle\langle E_j| \end{aligned}$$

account for the optical transition ³A ↔ ³E in the *j*th NV⁻- center. The term H_{field} describes the interaction of the electric moments of the NV⁻- centers with the classical laser fields, $\mathcal{E}_{1,2}^{(0,-1)}$, with frequencies $\omega_{1,2}^{(0,-1)}$, polarized in the *x*-direction; H_{cavity} describes their

interaction with the optical cavity mode polarized in the z -direction; ϵ is the “electric field amplitude for one photon in the cavity”.

The idea of the approach remains the same as in the case of RF control of the NV^- -N coupling. For example, in order to induce the transition $(A; M_z = 0) \leftrightarrow (E)$ in the NV^- -center 1, we switch on the laser field $\mathcal{E}_1^{(0)}$, which is tuned to the frequency $\omega_1^{(0)} = \omega_c - E$. After performing the unitary transformation with $U = U_{\text{cavity}}U_0$, where $U_{\text{cavity}} = \exp[i \int^t dt H_{\text{cavity}}]$, and $U_0 = \exp[iH_0t]$, and then a RWA, the resulting term in the Hamiltonian will be,

$$H_{\text{eff},1}^{(0)} = -g_{\text{eff},1}^{(0)}(a^\dagger \sigma_1^- + a \sigma_1^+), \quad g_{\text{eff},1}^{(0)} = \frac{g_{1z}^{(0)} \epsilon g_{1x}^{(0)} \mathcal{E}_1^{(0)}}{\omega_c}, \quad (20)$$

and similarly for the rest of the transitions. As in [27], the coupling strength is proportional to the classical field amplitude. To target only one NV^- -center, we now have two strategies. One is to reproduce our earlier approach and apply a non-uniform electric field. Then, due to the Stark shift, the resonance frequency of a given NV^- -center will depend on its location, and the control is realized by applying uniform optical fields at specific frequencies. (Of course, due to the non-uniform static magnetic field applied to the system the $(A \leftrightarrow E)$ transition frequencies will already differ for different NV^- -centers, but the difference is negligible.)

The other strategy is to apply laser fields locally. Given the transition wavelength 637 nm this may either put a lower limit on the spacing between NV^- -centers, or require e.g. using evanescent modes in waveguides.

The interactions (20) can produce single-qubit rotations [8, 27]. In our scheme they can be done more easily with RF pulses. On the other hand, two-qubit gates for different NV^- -centers require long-range coupling, which can be achieved through virtual excitations in the cavity. For example, if we only apply the fields $\mathcal{E}_1^{(0)}$ and $\mathcal{E}_2^{(0)}$, and eliminate the cavity modes in linear order by the Schrieffer-Wolff transformation[28], we obtain the effective interaction

$$H_{\text{eff},12}^{(00)} = \frac{2g_{\text{eff},1}^{(0)}g_{\text{eff},2}^{(0)}}{\omega_c - E}(\sigma_1^- \sigma_2^+ + \sigma_2^- \sigma_1^+). \quad (21)$$

We will also need transitions between the 3A levels $M_z = 0(-1)$ and the 3E state. They can be realized by applying another laser field with x -polarization and at a corresponding resonant frequency ≈ 470 THz ($\lambda = 637$ nm). The cavity degrees of freedom or other NV^- -centers will not be involved.

Using (21), we can produce, e.g., an entangling transformation

$$(\alpha|M_z = 0\rangle_1 + \beta|M_z = -1\rangle_1) \otimes |M_z = 0\rangle_2 \rightarrow (\alpha|M_z = 0\rangle_1 \otimes |M_z = -1\rangle_2 + \beta|M_z = -1\rangle_1 \otimes |M_z = 0\rangle_2). \quad (22)$$

To achieve this, we perform the following set of operations:

- 1) π -pulse between $|M_z = 0\rangle_1$ and $|E\rangle_1$; the result is $(\alpha|E\rangle_1 + \beta|M_z = -1\rangle_1) \otimes |M_z = 0\rangle_2$;
- 2) π -pulse of the interaction (21), resulting in $(\alpha|M_z = 0\rangle_1 \otimes |E\rangle_2 + \beta|M_z = -1\rangle_1 \otimes |M_z = 0\rangle_2)$;
- 3) π -pulse between $|E\rangle_2$ and $|M_z = -1\rangle_2$; the outcome is $(\alpha|M_z = 0\rangle_1 \otimes |M_z = -1\rangle_2 + \beta|M_z = -1\rangle_1 \otimes |M_z = 0\rangle_2)$, as required. After enabling the effective NV^- - NV^- -coupling through the cavity, the operations on N impurities coupled to different NV^- - centers can be realized in the same way as in Ref. [23].

Although the above procedure nicely demonstrates the possibility of using the cavity to perform two-qubit gates, it takes any state of the form $(\alpha|M_z = 0\rangle_1 + \beta|M_z = -1\rangle_1) \otimes |M_z = -1\rangle_2$ outside the computational basis. Instead, the C-phase gate could be implemented as follows:

- 1) π -pulse between $|M_z = 0\rangle_1$ and $|E\rangle_1$;
- 2) 2π -pulse of the interaction (21);
- 3) π -pulse between $|M_z = 0\rangle_1$ and $|E\rangle_1$.

An inspection of the above procedure shows that the three states $|M_z = 0\rangle_1|M_z = 0\rangle_2$, $|M_z = -1\rangle_1|M_z = 0\rangle_2$ and $|M_z = -1\rangle_1|M_z = -1\rangle_2$ are left unchanged at the end of the procedure, whereas the state $|M_z = 0\rangle_1|M_z = -1\rangle_2$ acquires a minus sign (note that we are not including here the phases accumulated as a result of single-qubit Larmor precession). This two-qubit gate, along with single-qubit rotations, form a universal set of gates for quantum computing.

The requirements to the optical cavity are high, but not impossible. In order to resolve ~ 1.5 GHz against the ~ 470 THz resonant frequency, the quality factor of the cavity should be at least of order 3×10^5 . We could somewhat improve the situation by adding one more step and swapping the states $M_z = 0$ and $M_z = 1$. This can be done again using the RF field $B_y(t)$ (Eq. (8)), this time with the frequency $\omega'_y = D + \kappa B_z$ (of order of 4.5 GHz). This increases the difference of the states involved in the optical coupling from ~ 1.5 GHz to ~ 3 GHz.

VI. CONCLUSIONS

We propose a frequency-controlled approach to coherent manipulation of spin states of NV^- -centers and NV^- -N complexes in diamond. It allows to address different spins through the difference in their resonance frequencies, induced by a static non-uniform magnetic field. The time-domain manipulations are performed using uniform RF fields. Different NV^- -centers and NV^- -N complexes can be coupled optically through the virtual excitations in an optical cavity. Here both frequency control with spatially uniform AC fields and with local AC fields are possible. The required cavity quality factor is high, but achievable. Our results show that small-scale quantum information processing devices based on impurity spins in diamond may be feasible in the near future.

Acknowledgements.— We are greatly indebted to A. Greentree and R. Hanson for very helpful remarks and suggestions, and a thorough reading of the manuscript. This work was supported in part by the ARO, LPS, NSA, and by the NSF Grant No. EIA-0130383. A.Z. acknowledges partial support by the NSERC Discovery Grants Program. S.A. was supported by the JSPS.

-
- [1] E. van Oort, P. Stroomeer, and M. Glasbeek, Phys. Rev. B **42**, 8605 (1990).
 - [2] F. Jelezko, T. Gaebel, I. Popa, M. Domhan, A. Gruber, and J. Wrachtrup, Phys. Rev. Lett. **93**, 130501 (2004).
 - [3] R. Hanson, O. Gywat, and D. Awschalom, Phys. Rev. B **74**, 161203(R) (2006).
 - [4] T. Gaebel et. al., Nature Physics **2**, 408 (2006).
 - [5] R. Hanson, F. Mendoza, R. Epstein, and D. Awschalom, Phys. Rev. Lett. **97**, 087601 (2006).
 - [6] L. Childress et. al., Science **314**, 281 (2006).
 - [7] M. Lukin and P. Hemmer, Phys. Rev. Lett. **84**, 2818 (2000).
 - [8] M. Shahriar, P. Hemmer, S. Lloyd, P. Bhatia, and A. Craig, Phys. Rev. A **66**, 032301 (2002).
 - [9] A. Greentree et. al., J. Phys.: Condens. Matter **18**, S825 (2006).
 - [10] A. A. Kaplyans, V. I. Kolyshkin, and V. N. Medvedev, Sov. Phys. Solid State **12**, 1193 (1970).
 - [11] G. Davies and N. B. Manson, Ind. Diamond Rev. **No. 2**, 50 (1980).
 - [12] D. Redman, S. Brown, and S. C. Rand, J. Opt. Soc. Am. B **9**, 768 (1992).

- [13] P. Tamarat et. al., Phys. Rev. Lett. **97**, 083002 (2006).
- [14] J. H. N. Loubser and J. A. van Wyk, Rep. Prog. Phys. **41**, 1201 (1978).
- [15] N. R. S. Reddy, N. B. Manson, and E. R. Krausz, J. Lumin. **38**, 46 (1987).
- [16] E. van Oort, N. B. Manson, and M. Glasbeek, J. Phys. C **21**, 4385 (1988).
- [17] D. A. Redman, S. Brown, R. H. Sands, and S. C. Rand, Phys. Rev. Lett. **67**, 3420 (1991).
- [18] W. Smith, P. P. Sorokin, I. L. Gelles, and G. J. Lasher, Phys. Rev. **115**, 1546 (1959).
- [19] D. A. Lidar and J. H. Thywissen, J. Appl. Phys. **96**, 754 (2004).
- [20] J. Q. You and F. Nori, Physics Today **58**, No. **11**, 42 (2005).
- [21] Y. Liu, L. F. Wei, J. S. Tsai, and F. Nori, Phys. Rev. Lett. **96**, 067003 (2006).
- [22] S. Ashhab, J. R. Johansson, A. M. Zagoskin, and F. Nori, quant-ph/0702032 (2007).
- [23] A. M. Zagoskin, S. Ashhab, J. R. Johansson, and F. Nori, Phys. Rev. Lett. **97**, 077001 (2006).
- [24] Y. Makhlin, G. Schon, and A. Shnirman, Rev. Mod. Phys. **73**, 357 (2001).
- [25] A. Blais, A. M. van den Brink, and A. M. Zagoskin, Phys. Rev. Lett. **90**, 127901 (2003).
- [26] A. Wallraff et. al., Nature **431**, 162 (2004).
- [27] A. Imamoglu et. al., Phys. Rev. Lett. **83**, 4204 (1999).
- [28] J. R. Schrieffer and P. A. Wolff, Phys. Rev. **149**, 491 (1966).